



ClareVision DDNS Product Bulletin

Content

Introduction.....	1
To begin.....	1
Accessing an account.....	1
Configuring the router.....	2
Configuring the device.....	2
Viewing the devices.....	3
ClareVision application.....	3
Customer support information.....	4

Introduction

The ClareVision DDNS is a free USA-based DDNS service. This service lets you view and monitor the devices in your home from an Apple or Android device. The ClareVision DDNS manages, tracks, and updates the IP information daily (6 a.m. EST) to ensure an uninterrupted use of your devices. This service is compatible with all ClareVision and third-party equipment.

To begin

Accessing an account

When creating or logging into the account, make sure that you are connected to the router in the home. Launching the service will automatically connect it to the external IP address from the router.

To access an account:

1. On your web browser, type **www.myclarevision.com**.
2. Login to register an account. If this is a first-time access, the site will prompt you for a domain name before continuing.

clarecontrols™

User Settings
Domains
Logout

Domain Name Creation

Enter a new domain name below.

You must create a domain name to continue.

Domain name must start with (a-z, 0-9). Cannot end or start, but may contain a hyphen and is not case-sensitive.

yourname . myclarevision.com IP: 72.91.2.194 Request Domain

3. Select the domain name you want – for example, *yourname.myclarevision.com*. Do not change the myclarevision.com box.
4. Click **Request Domain**.

Configuring the router

Before connecting the device to the DDNS, you must configure the router and open ports. Opening the ports (forwarding) allows users to access the device through the Internet.

Open port 80 (HTTP), port 8000 (server), and 8554 (RTSP).

Note: When configuring the router, it is important to note that every model is different. You will need to consult the documentation for the router that you are using to understand port forwarding and basic configuration for that router.

Configuring the device

Once you have chosen a domain name, you can configure the device.

To configure the device:

1. Access the device you are going to configure.
2. On the menu bar, click **Configuration**, and then select the **DDNS** tab and fill in the DDNS information.

TCP/IP	Port	DDNS	PPPoE	SNMP	802.1X	QoS	FTP	UPnP™	Email	NAT
--------	------	-------------	-------	------	--------	-----	-----	-------	-------	-----

<input checked="" type="checkbox"/> Enable DDNS
DDNS Type <input type="text" value="CVDDNS"/>
Server Address <input type="text" value="www.myclarevision.com"/>
Domain <input type="text" value="yourname.myclarevision.com"/>
Port <input type="text" value="80"/>
User Name <input type="text"/>
Password <input type="text"/>
Confirm <input type="text"/>

- a. Ensure the DDNS service is enabled click **Enable DDNS**.
- b. From the **DDNS Type** dropdown list, select the **CVDDNS** service.
- c. In the **Server Address** field, enter **www.myclarevision.com**.
- d. In the remaining fields, enter the domain, user name, and password that you have selected, and then click **Save**.

Viewing the devices

ClareVision application

After configuring the devices, use the ClareVision app to monitor them.

To use the ClareVision app:

1. Install the ClareVision app on your Apple or Android device.
2. Log in using the same information that you chose for the myclarevision site.
3. Access the **Device Information** tab on the menu and select the device you want to configure.
4. Make sure that all of the details in the DDNS tab match the ones entered in the device configuration.

Note: You must enter a device alias. This is any name that you want for this particular device – for example, hallway camera, Benny’s Garage, or 32 nvr.

5. Make sure that everything is filled in correctly, and then repeat steps 1 through 4 for each device.

Alias	32 nvr
Register Mode	IP/Domain
Address	10.100.30.229
Port	8000
User Name	clareadmin
Password	*****
Camera No.	5

Start Live View

Once the devices are configured and set to the ClareVision DDNS you will be able to view and monitor your devices from the ClareVision app.

Customer support information

For questions about Clare Controls products, please contact us at:

Clare Controls Inc., 7519 Pennsylvania Avenue, Suite 104, Sarasota, FL 34243

Support: 941.404.1072

Fax: 941.870.9646

claresupport@clarecontrols.com

www.clarecontrols.com