

B5512 Control Panels

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Supports up to 48 points using a combination of hardwired or wireless points for installation flexibility and up to 4 areas with perimeter and interior control
- ▶ On-board Ethernet port for Conettix IP alarm communication and remote programming, compatible with modern IP networks including IPv6/IPv4, Auto-IP, and Universal Plug and Play
- ▶ Installer-friendly features including on-board USB for easy on-site RPS programming, plus plug-in PSTN and Cellular communication modules for simple installation and future proof upgrades
- ▶ Notifications with email and text messaging, and the Remote Security Control app for Android and iOS mobile devices
- ▶ Programmable keypad shortcuts, situation sensitive on-screen help, and a bilingual user interface make system operation simple and easy

The B5512 Control Panel integrates intrusion and residential fire, providing one simple user interface for both systems. The B5512 provides up to 48 individually identified points that can be split into 4 areas. The control panel includes a built-in Ethernet port for IP network communications, and is compatible with modules that send events to selected public switched telephone network (PSTN), IP network, or cellular network destinations through four programmable route groups. With the B5512, you can monitor doors, windows, and motion within areas like showrooms or those that hold inventory. Each user can have a personalized passcode, a wireless keyfob, and a credential to control the system.

Use programmable authority levels with restricted privileges to provide service, security, and cleaning personnel with full or limited access. Use the three programmable outputs (expandable up to 43) to turn on lights or lock and unlock doors. Users can:

- Turn on the system to secure the stockroom while you conduct daily business.
- Perform tests to ensure your system is working properly.
- Set your system to alarm immediately if a door opens.
- Activate the Watch feature so a tone sounds whenever a customer enters.
- Set a schedule for your system to automatically turn on at closing time.
- Use wireless security options to customize your system.

Central monitoring stations provide 24-hour system monitoring with access to vital services. Professional security personnel can test the system, monitor system activity, and alert the police, fire department, or other emergency response teams if necessary.

Functions

Programmable outputs

- 500 mA not to exceed 1.3 A total current for a burglary system, or not to exceed 1.0 A total current for household fire applications
- 800 mA auxiliary power at 12 VDC
- Four alarm-output patterns
- Programmable bell test
- Three programmable outputs; one high current using a relay, and two trigger outputs
- Output A contact rating is 3 Amps

System response

- High-performance micro-controller provides industry leading system response
- 20 custom point indexes
- Selectable point response time
- Cross point capability
- Fire alarm verification
- Dangerous gas indicator includes carbon monoxide (NFPA 720)
- Watch mode
- Scheduled events (SKEDs) perform several functions, such as turn on (arm) the system, turn off (disarm) the system, bypass and unbypass points, and control relays

User interface

- Supervision of up to 8 keypads
- Custom keypad text is fully programmable through RPS
- Full function menu including custom functions
- Authority by area and 32 character name for each user
- 14 custom authority levels control user's authority to change, add, or delete passcodes to disarm or bypass areas; and to start system tests
- Programmable primary and secondary language by user and keypad; select from English, Spanish, French, and Portuguese

Area configurations

Area programming offers a wide selection of different system configurations. Make area arming conditional on other areas (master or associate), if desired. You can configure any area for perimeter and interior arming, not requiring a separate area for this function. Link multiple areas to a shared area which is automatically controlled (hallway or lobby). For higher security applications, the Area Re-Arm feature guarantees that areas are always rearmed, and are disarmed for no longer than a specific, configurable, amount of time (for example, service time).

Custom functions

For added convenience, the installer can program custom functions that allow customers to complete complex tasks with fewer keystrokes. For example, a custom function can bypass a group of points and arm the system, allowing the user to perform this function with one easy command. Installers can use custom functions to control a particular room. Customers activate custom functions with a keypad, with a keyfob, by faulting a point, or automatically as a scheduled event (SKED).

Passcode security

- Two-Man Rule - Requires two people with two unique passcodes to be present at the time of opening.
- Early Ambush - Allows users to verify that the facility is safe by requiring two passcodes. The control panel sends a duress event if the user does not enter the passcode a second time after inspecting the premises.

Easy exit control

The control panel changes from one On (armed) state to another On (armed) state without turning off (disarming) the system. For example, if you change the state from Part On (Perimeter Arm) to All On (Master Arm), the control panel complies and reports the change. Easy Exit Control reduces the number of keystrokes, simplifying system operation.

Programmable passcode-controlled menu list

Passcode-controlled shortcuts provide users only with the options and information pertinent to them, simplifying system operation.

Flexible control

The system provides the flexibility to choose added convenience or high security. For example, you can restrict to a keypad's immediate local area turning on (arming) and turning off (disarming) the system with a passcode, even if the user has access to other areas. This is particularly useful for high security areas, where a user may have access to the area, but would prefer to only turn off (disarm) the area individually rather than with the rest of the system. Another option is to program the system to turn off all areas the user can access from any keypad.

Monitor Delay

While disarmed, this feature sends a burg supervisory report to the central station receiver if a point is faulted for a configurable amount of time (for example, a door left open).

System users

The system supports up to 50 users. Each user can have a personalized passcode, a wireless keyfob, and a credential to control the system. User passcodes contain three to six digits. You can assign passcodes to one of 14 customized authority levels in each area that can be restricted to operate only during certain

times. Programmable primary and secondary language by user and keypad; select from English, Spanish, French, and Portuguese.

Communication formats

The control panel prioritizes and sends reports to four route groups. Network communication uses the Modem4 communication format, whereas phone communication uses Contact ID or Modem4 communications formats. Each group has a programmable primary and backup destination. The control panel provides flexible communications for most central stations with reporting capabilities such as:

- Individual point numbers
- Opening or closing reports by user and area number
- Remote programming attempts
- Diagnostic reports

IP communication

The control panel uses the optional on-board Ethernet connector, B440 Conettix Plug-in Cellular Communicator, B441 Conettix Plug-in CDMA Cellular Communicator, B442 Plug-in GPRS Cellular Communicator (Latin America), B443 Plug-in HSPA+ Cellular Communicator (Canada), or B426 Conettix Ethernet Communication Module to communicate with a Conettix D6600 or a Conettix D6100IPv6 Communications Receiver/Gateway. Using Conettix IP communication offers a secure path that includes anti-replay/anti-substitution features and provides enhanced security with AES 256-bit encryption. You can use the Ethernet connection for remote programming.

The control panel supports Domain Name System (DNS) for both remote programming and central station communication. DNS provides ease of use, eliminating the need to use static IP addresses as your reporting destination, and accommodates a simple solution for central station disaster recovery. IP Setup is available via the keypad Installer menu and the remote programming software, eliminating the need to use complicated internet programming tools such as ARP and Telnet. The control panel supports both IPv6 and IPv4 networks.

For more information on the enhanced communications capabilities, refer to *RPS Help* or the *Control Panels Program Entry Guide*.

Communication paths

The control panel accommodates up to four separate phone and four separate network paths to the central station receiver. When resetting alarms or turning a system on and off, the user is identified by name and number.

Personal notification

The control panel can send text messages and emails for personal notification over Ethernet or using a cellular communicator. You can configure up to 16 destinations using a combination of cellular phone numbers and email addresses.

Firmware updates

Remote firmware updates through Remote Programming Software (RPS) using the RPS Firmware Update Wizard. The Firmware Update Wizard uses the on-board USB connection or optional IP connection (on-board Ethernet connection, B426 Conettix Ethernet Communication Module, B440 Conettix Plug-in Cellular Communicator, B441 Conettix Plug-in CDMA Cellular Communicator, B442 Plug-in GPRS Cellular Communicator (Latin America), B443 Plug-in HSPA+ Cellular Communicator (Canada)) to transmit the updates.

- Control panel updates. Remotely update the control panel firmware for easy feature enhancements without replacing ROM chips.
- Module update support. Remotely update the firmware on connected SDI2 modules for easy feature enhancements without visiting each individual module.

A wide variety of input options

Each point:

- Accommodates normally-open (NO) and normally-closed (NC) devices with end-of-line (EOL) resistor supervision.
- Accepts programming for fire, gas, fire supervisory, or intrusion applications.
- Supports hardwired and wireless devices.
- Supports IP cameras by Bosch as point sources.

Security and fire detection

The control panel provides eight on-board points, and up to 40 additional off-board points (depending on model and expansion interfaces). You can program individual points to monitor some types of burglar alarms, fire alarms, and supervision devices.

Event log

The event log stores up to 255 local and reported events. The event log includes time, date, event, area, point, and user. View the event log from a keypad or use RPS to remotely retrieve event information. When the event log reaches a programmed threshold of stored events, it can send an optional report to a receiver.

Scheduled events (SKEDs)

Scheduled events (SKEDs)

The internal clock and calendar start individually scheduled events (SKEDs). SKEDs perform functions such as turn on or off, relay control, or point bypassing.

The control panel offers:

The control panel offers:

- Five scheduled events with up to 25 different functions
- Four opening windows and four closing windows
- Four user windows
- Day-of-week, date-of-month, or holiday only schedules
- One holiday schedule of 366 days (leap year)

Programming

Installers can perform limited programming on-site with a keypad (critical parameters; such as account IDs, central station and RPS IP addresses and phone numbers, reporting formats, and more). They can also do full programming on-site or remotely (attended or unattended) with RPS. A programmable system passcode prevents unauthorized remote programming.

Diagnostics

Keypads and RPS offer diagnostic help for monitoring and troubleshooting. The diagnostics features allow you to view the status of the on-board Ethernet connection, plug-in communicators, and SDI2 devices, including inputs, outputs, and RF. The features provide the status of the control panel and its connected devices, such as firmware version, power, and missing conditions. View the status of each area. Diagnostics also include connection data for connected wireless and Ethernet devices.

Certifications and approvals

Region	
US	UL 365 - Police Station Connected Burglar Alarm Units and Systems
	UL 609 - Local Burglar Alarm Units and Systems
	UL 636 - Holdup Alarm Units and Systems
	UL 985 - Household Fire Warning System Units
	UL 1023 - Household Burglar Alarm System Units
	UL 1076 - Proprietary Burglar Alarm Units and Systems
	UL 1610 - Central Station Burglar Alarm Units
	FCC Part 15 Class B
Canada	CP-01-2010-Control Panel Standard - Features for False Alarm Reduction
	CAN/ULC S303 - Local Burglar Alarm Units and Systems
	CAN/ULC S304 - Signal Receiving Centre and Premise Alarm Control Units
	CAN/ULC S545, Residential Fire Warning System Control Units
	ULC-ORD C1023 - Household Burglar Alarm System Units
	ULC-ORD C1076 - Proprietary Burglar Alarm Units and Systems
CP-01-2010-Control Panel Standard - Features for False Alarm Reduction	

Region	Certification	
USA	UL	20130806-S1871
	CSFM	7167-1615:0247 7167 -- CONTROL UNIT (HOUSEHOLD)
Canada	ULC	20130806-S1871

Installation/configuration notes

Compatible products

Keypads

B942/B942W Touch Screen Keypad
 B930 ATM Style Alphanumeric Keypad (SDI2)
 B921C Two-line Capacitive Keypad
 B920 Two-line Alphanumeric Keypad (SDI2)
 B915 Basic Keypad

Transformers

CX4010 Plug-in Transformer (18 VAC 22 VA 60 Hz)
 ICP-TR1822-CAN Plug-in Transformer (110 VAC primary, 18 VAC 22 VA secondary)

Enclosures

B10 Medium Control Panel Enclosure
 B11 Small Control Panel Enclosure
 B12 Mounting Plate for D8103 Enclosure
 D2203 Enclosure
 D8103 Universal Enclosure (requires a B12)
 D8108A Attack Resistant Enclosure (requires a B12)
 D8109 Fire Enclosure (requires a B12)

Accessories

B56 Keypad Surface Mount Box
 B96 Keypad Trim Bezel
 B99 USB Direct Connect Cable
 B501-10 Interconnect wiring cables (pack of 10)

Detectors

D285/TH Photoelectric Smoke Detector Heads
 FCC-380 Carbon Monoxide Detector
 Bosch conventional detectors, including Professional Series, Blue Line Gen2, Blue Line, Classic Line, Commercial Line, and Ceiling Mount motion detectors, as well as glass break, seismic, request-to-exit, photoelectric, heat, and smoke detectors.

Modules

B201 2-wire Powered Loop Module
 B208 Octo-input Module
 B308 Octo-output Module
 B426 Conettix Ethernet Communication Module
 B430 Plug-in Telephone Communicator
 B440 Conettix Plug-in Cellular Communicator
 B441 Conettix Plug-in CDMA Cellular Communicator
 B442 Plug-in GPRS Cellular Communicator (Latin America)

B443 Plug-in HSPA+ Cellular Communicator (Canada)
 B450 Conetix Plug-in Communicator Interface
 B520 Auxiliary Power Supply Module
 B810 wireless receiver (RADION)
 B820 SDI2 Inovonics Interface Module
 D113 Battery Lead Supervision Module
 D125B Dual Class B Initiating Module
 D129 Class A Initiating Module
 D130 Auxiliary Relay Module
 D132A Smoke Detector Reversing Relay Module
 D133/D134 Relay Module
 D185 Reverse Polarity Signaling Module
 D192G Class "B", Style Y Bell Circuit Supervision

Programming

Remote Programming Software (RPS or RPS-LITE) v5.17 or higher

Conetix receivers

(Managed and configured with Conetix D6200 Programming/ Administration Software v2.00)

Conetix D6600 Communications Receiver/Gateway (with only D6641 line cards installed) with CPU version 01.10.00

Conetix D6100IPv6 Communications Receiver/Gateway with CPU version 61.10.00

Conetix D6100i Communications Receiver/Gateway with CPU version 61.10.00

RADION wireless from Bosch

B810 wireless receiver (RADION)
 RFBT-A bill trap
 RFDL-11-A TriTech motion detector
 RFDW-RM-A recessed mount door/window contact
 RFDW-SM-A surface mount door/window contact
 RFGA-A glass break detector
 RFIN-A inertia detector
 RFKF-A two-button keyfob
 RFKF-FB-A four-button keyfob
 RFKF-TB-A two-button keyfob
 RFPB-SB-A single-button panic
 RFPB-TB-A two-button panic
 RFRP-A repeater
 RFSM-A smoke detector
 RFPR-12-A PIR motion detector

RFPR-C12-A PIR curtain motion detector

RFUN-A universal transmitter

Inovonics Wireless

B820 SDI2 Inovonics Interface Module
 ENKIT-SDI2 SDI2 Inovonics Interface and Receiver Kit. Includes B820 and EN4200
 EN1210 Universal Transmitter (Single-input)
 EN1210EOL Universal Transmitter with EOL Resistor
 EN1210W Door-Window Transmitter with Reed Switch
 EN1215EOL Universal Transmitter with Wall Tamper, Reed Switch, and EOL Resistor
 EN1223D Water-resistant Pendant Transmitter (Double-button)
 EN1223S Water-resistant Pendant Transmitter (Single-button)
 EN1224-ON Multiple-Condition Pendant Transmitter
 EN1233D Necklace Pendant Transmitter (Double-button)
 EN1233S Necklace Pendant Transmitter (Single-button)
 EN1235D Beltclip Pendant Transmitter (Double-button)
 EN1235DF Fixed-location Transmitter (Double-button)
 EN1235S Beltclip Pendant Transmitter (Single-button)
 EN1235SF Fixed-location Transmitter (Single-button)
 EN1247 Glass-break Detector Transmitter
 EN1249 Bill Trap Transmitter
 EN1242 Smoke Detector Transmitter
 EN1260 Wall Mount Motion Detector
 EN1261HT High Traffic Motion Detector
 EN1262 Motion Detector with Pet Immunity
 EN1265 360° Ceiling Mount Motion Detector
 EN4200 Serial Receiver
 EN5040-T High Power Repeater with Transformer

Parts included

The B5512 includes the following parts:

Quant.	Component
1	B5512 board
1	Literature pack <ul style="list-style-type: none"> • UL Installation Instructions • Owner's Manual • Release Notes • SIA Quick Reference Guide
1	Literature CD containing product literature

The B5512E includes the following parts:

Quant.	Component
1	B5512E board (without on-board Ethernet port)
1	Literature pack <ul style="list-style-type: none"> • UL Installation Instructions • Owner's Manual • Release Notes • SIA Quick Reference Guide
1	Literature CD containing product literature

For kits, refer to *Special (B Series Kits)* on the Documents tab of the control panel's Product Page at us.boschsecurity.com.

Technical specifications

Communications

Ethernet	One on-board Ethernet connector*
----------	----------------------------------

Environmental considerations

Relative humidity	5% to 93% at +90°F (+32°C), non-condensing
Temperature (operating)	+32°F to +122°F (0°C to +49°C)

Number of...

Areas	4
Custom functions	4
Events	Up to 255
Passcode users	50, plus 1 Installer passcode
Points	48 (8 on-board, up to 40 off-board)
Programmable outputs	43 (3 on-board, up to 40 off-board)
RF points	40
SKEDs	5

Power Requirements

Current draw (maximum)	Idle 125 mA; Alarm 155 mA
Output (alarm)	1.3 A at 12 VDC
Output (auxiliary, continuous power, and switched auxiliary combined)	800 mA at 12 VDC nominal
Voltage (operating):	12 VDC nominal
Voltage (AC)	CX4010 Plug-in Transformer (18 VAC 22 VA 60 Hz) or ICP-TR1822-CAN Plug-in Transformer (110 VAC primary, 18 VAC 22 VA secondary)

*The "E" control panels do not include an on-board Ethernet connector.

Trademarks

All hardware and software product names used in this document are likely to be registered trademarks and must be treated accordingly.

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com