



VAPORESSO

Target Pro Mod Quick Guide

Target Pro Mod

Thank you for choosing Vaporesso Products!

With an elegant and futuristic design, Target Pro Mod adopts variable temperature control function and has very simple operation. Be able to handle up to 75w with high-drain 18650 battery and also includes a micro USB charging port. Its ceramic coated surface with a leather feel in your fingers, it looks as great as it feels.

Please read this manual carefully to ensure proper use. For additional information or questions regarding to this product or its use, please visit www.vaporesso.com

Characteristic:

- Target Pro Box Mod Output 75W supports VT: 0.05Ω-1.0Ω VW: 0.15Ω-3Ω
- 4 Adjusting modes: Variable Temperature: Ni/SS/Ti/TCR Variable Wattage, Stainless Steel, Titanium
- TCR Mode Available at Firmware Update
- Automatic Atomizer Recognition
- Aqueous Ceramic Coated Surface

Package include

- 1 Target Pro Mod
- 1 USB cable
- 1 User Manual

Target Pro Mod

Dimension: 92x48x27 mm
Weight: 180g
Temperature Range: 100°C-315°C/200F-600F
Output Wattage: 5w to 75w
Suitable atomizer: VT: 0.05Ω-1.0Ω VW: 0.15Ω-3Ω
Output Modes: VT/Ni/SS/Ti/TCR
Standby Current: < 50uA
Voltage range: 0-9V
Battery Cell: Lithium 18650
Casting: Zinc Alloy and stainless steel
Thread: 510 thread
Display: OLED
USB Updatable and customizable firmware



Target Pro Mod Operation Guide

- 1. Switch on/off:** after a battery is installed, press the power button 5 speedy times to switch on the mod, "Vaporesso" will appear on the screen.
- 2. Screen Display:** after switch on, OLED displays voltage, resistance value, battery level, temperature, output wattage; the display will shut off if unused for 15s, the screen will be relit by pressing the fire button.
- 3. Automatic atomizer recognition:** the mod will read the coil's resistance as soon as the connection is detected. It will also recognize coil type, when a kanthal coil is used, the mod will shift from TC to wattage mode automatically.
- 4. To vape:** Long pressing the power button to vape, it will initiate 10s' counting down to limit maximum time for one puff; pressing longer than 10s will shut it down, "over 10s" will be shown on the screen.
- 5. Adjust wattage:** Press the " + " - " to adjust the wattage at 0.1 increment, long-press will adjust at an accelerated rate.
- 6. To rotate the screen display:** fast click fire button 3 times.

7. To lock the diameters: Press the " + " steadily while press the power button simultaneously, " SYSTEM LOCKED" appears on the screen. Repeat the motion to unlock.

8. Charging: Plug in the Micro USB cable to charge the battery, OLED display current battery level (0%, 20%, 50%, 80%, and 100%), The display will remain lit while charging.

Temperature Control

1. Switch 4 modes: Press " + " - " together to switch between wattage mode and different temperature control modes.

2. Adjust temperature: At temperature control mode, press the " + " - " to adjust the temperature at 10°F or 5°C, long-press will adjust at an accelerated rate.

3. Lock/Unlock resistance: At temperature control, press the " - " and power button simultaneously for 2s will lock/unlock the resistance level, " " will appear on the display. Attach a new atomizer will not change the locked resistance.

4. Automatic atomizer recognition: To achieve better temperature control effect, the mod will ask the user if

the new atomizer is attached. " OLD LOAD-, NEW LOAD + " will appear on the display. If a new atomizer is attached, press " + ", the mod will read new resistance; if not, press " - ", the mod will read at locked resistance.

5. Firmware update and customizing: The firmware can be updated and customized through a simple software that can be downloaded directly from our website. The software will be made to run on Windows systems and will be available in Chinese or English. It will also include a "help" sections for urgent questions. The directions on how to use our software will be found on our website and Facebook page.

Target Pro Mod Protection functions

- Over - temperature protection (PCBA temperature less than 65°C)
- Low battery protection
- Short-circuit protection
- Low resistance protection (Resistance $\geq 0.13\Omega$)
- Reverse connection of the battery power terminal
- Over-charge protection and over discharge protection (2.9v-4.3v)
- No atomizer detection protection
- Over current protection

Caution

1. The Target Pro Mod is intended for usage by people over 18, NOT by non-smokers, children, pregnant or breastfeeding women, people with or at risk of heart disease, or people taking medication for depression or asthma. The electronic cigarette is not a smoking cessation device.
2. Please keep this unit out of reach of children or pets.
3. Please don't drop, throw or abuse your Target Pro , it may cause damage.
4. Please keep the battery dry.
5. Do not place it in extremely temperatures.
6. Do not try to disassemble the battery.
7. This device does not mean to be used as a nicotine replacement therapy for smoking cessation.

Beyond the ordinary