



Features

- Remote status and control of the PROACTIV system
- Protection from unauthorized use with key switch
- Local audible signal (can be silenced)
- Multiple language support on the user interface
- Local LED and LCD device test
- Supports NFPA 72 Style 4 or Style 6 SLC wiring
- Surface or recess wall mounting
- Convenient power in / power out connectors
- Local power supply monitoring input
- Robust fault-tolerant communications
- Ground fault detection

Listings/Approvals

- UL 864 9th Edition

Product Description

The PROACTIV® Remote Annunciator Module (RA) provides remote system status information and control of the PROACTIV system.

The RA can be mounted to a surface or recess style 4 gang back box and is connected to the ancillary SLC of the PROACTIV Fire Alarm Control Panel (FACP).

Function

The RA consists of an LCD display that provides access to the full operational status and standard control of the PROACTIV system.

The RA provides summary indicators for the alarm, supervisory and trouble status of the system. You can review the detailed event information within the system and can choose to acknowledge these events. An audible signal will sound when the PROACTIV system generates an alarm or trouble condition, and will continue to sound until the condition is acknowledged by an operator.

The RA can be used to manage the system remotely, using the following functions by pressing the assigned button:

Silence	Silences outputs on the entire system
Drill	Drills the entire system
Reset	Resets the system

Operation

The RA user interface is consistent with the PROACTIV FACP, providing a familiar look and feel across the whole PROACTIV system. The LCD display supports 21 by 8 characters.

The menu button allows you to view and set system and device configuration data via the LCD display. A test function is also provided on the RA to verify that the display and the keypad are functioning correctly.

PROACTIV® Remote Annunciator Module

VFA-213

Ordering Information

PROACTIV Ancillary Devices

Description	Model
Remote Annunciator (RA)	VFA-213
Fire Alarm Annunciator (FAA)	VFA-201
Fire Alarm Annunciator – Open Collector (FAA–OC)	VFA-205
Annunciator & Control Module (ACM)	VFA-203
Output Control Module – NAC (OCM–NAC) ¹	VFA-209
OCM–NAC Expansion Kit	PSP-2010
Output Control Module – Contact (OCM–Contact) ²	VFA-211
OCM–Contact Expansion Kit	PSP-2012
Agent Release Module (ARM) ³	VFA-207
ARM Expansion Kit	PSP-2014

¹ The OCM–NAC supports two expansion kits (PSP-2010) and includes one expansion kit as standard.

² The OCM–Contact supports two expansion kits (PSP-2012) and includes one expansion kit as standard.

³ The ARM supports two expansion kits (PSP-2014) and includes one expansion kit as standard.

Note: Not all of the above products are available in all regions.
Consult your local distributor or Xtralis office for more information.

Specifications

Device Type

PROACTIV Ancillary Device

Ancillary SLC

NFPA 72 Style 4 or Style 6 wiring
Supports a maximum of 31 nodes at a total distance of 3000 ft (1000 m)

Address Range

1 to 31

Power Supply

UL 1481 Listed 24 VDC power supply.

External Power Supply Monitoring

2k2 End of Line Resistor

Supply Voltage

24 VDC from FACP or UL 1481 Listed external power supply

Current Consumption @ 24 VDC

85 mA in Standby

100 mA in Alarm

Dimensions (WxH)

11.5 in x 5.4 in (292 mm x 138 mm)

Operating Environment

Dry Indoor

32°F to 120°F (0° to 49°C)

20% to 95% RH, non-condensing

Cable Termination

Screw terminal blocks 30–14 AWG
(0.2–2.0 mm²)

Mounting

UL Listed metallic Gang Back Box

www.xtralis.com

The Americas +1 781 740 2223 **Asia** +852 2297 2438 **Australia and New Zealand** +61 3 9936 7000
Continental Europe +41 55 285 99 99 **UK and the Middle East** +44 1442 242 330

The contents of this document are provided on an "as is" basis. No representation or warranty (either express or implied) is made as to the completeness, accuracy or reliability of the contents of this document. The manufacturer reserves the right to change designs or specifications without obligation and without further notice. Except as otherwise provided, all warranties, express or implied, including without limitation any implied warranties of merchantability and fitness for a particular purpose are expressly excluded.

This document includes registered and unregistered trademarks. All trademarks displayed are the trademarks of their respective owners. Your use of this document does not constitute or create a licence or any other right to use the name and/or trademark and/or label.

This document is subject to copyright owned by Xtralis AG ("Xtralis"). You agree not to copy, communicate to the public, adapt, distribute, transfer, sell, modify or publish any contents of this document without the express prior written consent of Xtralis.

Doc. no. 12702_01

Part: 29036

