



# ClareVue Lighting Accessory Switch and Dimmer Integration Notes

## Content

Preface .....	1
Introduction.....	1
Installing the switch or dimmer .....	2
Pairing and configuring the switch/dimmer in the apps.....	2
Using the device in the ClareHome app .....	6
Pairing and configuring the device in FusionPro.....	7
Contact information .....	9

**Last modified:** 11/30/30

## Preface

For information on Z-Wave and ClareHome, see [Installing Z-Wave with ClareHome](#).

## Notes

- When installing Z-Wave devices, ensure that there is nothing inhibiting their signal. Z-Wave relies on radio signals. Metal or thick walls may limit their signal strength.
- We recommend having 2 or more repeating Z-Wave devices.

## Introduction

The ClareVue Lighting Accessory Switches and Accessory Dimmers integrate with ClareHome via the Z-Wave network. Installers only need to pair (add) the switch or dimmer into ClareHome, then customize the device.

By integrating the accessory switches and dimmers into the ClareHome control system, your customers can control the associated lights from their Android or iOS devices.

## Installing the switch or dimmer

Only qualified installation technicians should install ClareVue lighting devices. Follow the installation and programming instructions that came with your ClareVue lighting devices.

## Pairing and configuring the switch/dimmer in the ClareHome App

After installing the accessory switch or dimmer, pair it.

**To pair the switch/dimmer using the ClareHome App:**


### Notes

- The pairing process is the same for each device.
- The accessory devices do not have a UI element in the ClareHome app.


**To pair the ClareVue device using ClareHome:**

**Note:** The pairing process is the same for each device.


1. Access the ClareHome Menu, then tap **Devices**.



2. On the upper right, tap **Manage Devices**.




3. Tap **Add Devices**.




4. Tap **Lighting**.




5. Tap **Z-Wave Device - Lighting**.




6. Tap **Add a Z-Wave Device**.



7. Tap **Start Discovery Mode**, then pair the device as per the manufacturer's instructions.



8. Enter a name for the device, select an area, then click **Save**.



9. Tap outside of the area drop-down and the Z-Wave device is ready to use.  
If using a dimmer, configure the settings.

**Note:** For scene, schedule, notification, and automation configuration, see [ClareHome App Guide \(DOC ID 1750\)](#).

## Using the device in the ClareHome app

Once deployed, the user can add the device to their space, then tap the lighting icon in the ClareHome app to display and operate the devices associated with the switch or dimmer, as shown below.

**Note:** Accessory devices do not have individual UI services. To use accessory devices from the app, control them through their associated master device.

Figure 1: Switch on and off





Figure 2: Dimmer at 60% and off




# Pairing and configuring the device in FusionPro


After installing the ClareVue device, pair it.

To pair the device with Fusion:


1. Go to the Summary page and click the **Devices** tab.




2. Click **Add Device**.




### 3. Click **Lighting**.



### 4. Click **Z-Wave Device - Lighting**.



5. Click **Start Discovery Mode** then pair the device as per the manufacturer's instructions.



## Notes

- Once paired, the light stops blinking.
- The Z-Wave lighting device dialog goes away when the device has been paired.

6. The device appears in the devices list.

## Contact information

Clare Controls, LLC.  
7519 Pennsylvania Ave, Suite 104  
Sarasota, FL 34243

General: 941.328.3991  
Fax: 941.870.9646  
www.clarecontrols.com

Integrator/Dealer Support: 941.404.1072  
claresupport@clarecontrols.com

Homeowner Support (ClareCare): 941.315.2273 (CARE)  
help@clarecontrols.com