



## Glass Break Detector

CHS-GLS-10



The Glass Break Detector identifies the sound of breaking glass. It can be mounted anywhere in the home that is from 4-25 ft from doors & windows to cover an entire room. Powered by a single 1550 mAH battery, the detector operates for up to 4-6 years. The glass break detector is ideal for extending coverage over a large area in a home or business.

- Sensor detects the sound of breaking glass
- 360° Omni-directional coverage
- Simple to pair using the enrollment button
- 4-6 year battery life on CR123A battery
- Low battery indication

### Technical Specifications

#### General

Dimensions	4.25 x 3.13 x 1.70" (10.8 x 7.95 x 4.3cm)
Battery Replacement	CR123A 1550 mAH
Mounting Fastener	# 4 or #6 screws, at least 3.3 feet from windows being protected, and 4 feet from sources of noise.

#### Sensor

Sensing Parameters	Glass break detection within 25ft
--------------------	-----------------------------------

#### Environmental

Operating Temperature	14° to 120°F without battery (-10° to 49°C)
Humidity	85% Non-condensing

By making home technology simple, Clare provides exclusive benefits to integrators, builders, and homeowners. We offer innovative home automation solutions, Class D amplifiers, media distribution, controllable lighting, and IP CCTV components. For more information, visit [clarecontrols.com](http://clarecontrols.com).