

COMPRESSOR DATA SHEET

Rotary Compressor: Variable Frequency Drive

MODEL DATA - FOR COMPRESSED AIR

1	Manufacturer: Mattei Compressors Inc.		
2	Model Number: OPTIMA 11		Date: Apr-15
	☒ Air-cooled ☐ Water-cooled	Type:	Vane
	☒ Oil-injected ☐ Oil-free	# of Stages:	1
3	Rated Operating Pressure	102	psig ^b
4	Drive Motor Nominal Rating	15	hp
5	Drive Motor Nominal Efficiency	92.4	percent
6	Fan Motor Nominal Rating (if applicable)	n/a	hp
7	Fan Motor Nominal Efficiency	n/a	percent
8*	Input Power (kW)	Capacity (acfm) ^{a,d}	Specific Power (kW/100 acfm) ^d
	14.14 Max	68.2	20.74
	13.24	64.6	20.49
	11.56	57.6	20.08
	9.97	50.1	19.87
	9.19	46.6	19.71
	8.45 Min	43.1	19.61
9*	Total Package Input Power at Zero Flow ^{c, d}	1.70	kW
10	Note: Graph is only a visual representation of the data in Section 8 Note: Y-Axis Scale, 10 to 35, + 5kW/100acfm increments if necessary above 35 X-Axis Scale, 0 to 25% over maximum capacity		

*For models that are tested in the CAGI Performance Verification Program, these items are verified by program administrator

Consult CAGI website for a list of participants in the third party verification program: www.cagi.org

NOTES:

- Measured at the discharge terminal point of the compressor package in accordance with ISO 1217, Annex E; acfm is actual cubic feet per minute at inlet conditions.
- The operating pressure at which the Capacity and Electrical Consumption were measured for this data sheet.
- No Load Power. In accordance with ISO 1217, Annex E, if measurement of no load power equals less than 1%, manufacturer may state "not significant" or "0" on the test report.
- Tolerance is specified in ISO 1217, Annex E, as shown in table below:
 NOTE: The terms "power" and "energy" are synonymous for purposes of this document.

Volume Flow Rate at specified conditions		Volume Flow Rate	Specific Energy Consumption	No Load / Zero Flow Power
m^3 / min	ft^3 / min	%	%	+/- 10%
Below 0.5	Below 15	+/- 7	+/- 8	
0.5 to 1.5	15 to 50	+/- 6	+/- 7	
1.5 to 15	50 to 500	+/- 5	+/- 6	
Above 15	Above 500	+/- 4	+/- 5	



ROT 031