


|                                   |                |
|-----------------------------------|----------------|
| <b>LMR BATTERY SPECIFICATIONS</b> | PART NUMBER    |
|                                   | <b>WV-6036</b> |

|                        |   |
|------------------------|---|
| COMPATIBLE RADIOS      | Motorola APX 6000, APX 6000XE, APX 7000, APX 7000XE, APX 8000   |
| REPLACES OEM BATTERY   | NNTN7034  |
| COMPATIBLE CHARGERS    | Endura EC1-MT19, EC1M-MT19, EC6M-MT19, TWC2M-MT19-D, TWC12M-MT19-D / Logic LEVCA-MT19 / Motorola adaptive IMPRES 1 and 2 chargers   |
| VOLTAGE                | 7.4V  |
| CAPACITY               | 4600 mAh / 34.0 Wh  |
| CHEMISTRY / CELL TYPE  | Li-Ion / Japanese   |
| BATTERY TYPE           | Smart (will recondition automatically in Impress 1, 2 Chargers)   |
| OPERATING TEMPERATURE  | -20° C to +60° C (discharge) / 0° C to +45° C (charge)  |
| CHARGE CYCLES          | 400   |
| CHARGE TYPE            | Rapid   |
| CONDITIONER COMPATIBLE | Yes   |
| THERMAL PROTECTION     | Yes   |
| HOUSING MATERIAL       | ABS   |
| HOUSING SEAL           | Ultrasonic weld   |
| METAL WELDING          | Pure nickel tabs w/ spot welder   |
| CLIP                   | N/A   |
| WARRANTY               | 12 months   |
| PRODUCT PHOTO          |  <div style="border: 1px dashed black; padding: 5px; display: inline-block; margin-left: 20px;"> <p>Dimensions (HxWxD):<br/>5.15" x 2.35" x 1.65"</p> </div> |