



Clare Siren with Battery Backup

CS-SRN-10



The Clare Siren with battery backup extends alarm sound to areas that are out of the audible threshold from the main security panel. The siren includes a backup on-board emergency battery that has a lifespan of up to 48 hours. Multiple sirens can be combined to cover larger areas.

- LEDs follow arming status and trouble conditions from control panel
- Wall-powered, with backup power built-in
- Cover tamper
- Wireless range of up 1000 ft
- Small form factor makes for easy installation in various locations

Technical Specifications

General

Dimensions	3 x 4 x 1.25" (7.6 x 10.2 x 3.17cm)
Back-up Battery Replacement	CR123A 1550 mAh, up to 48 hours non-rechargeable
Mounting Fastener	Secure with outlet plate mounting screw

Siren Specifications

Supervisory Time	64-68 minutes
Alarm Patterns	Follows panel siren ON/OFF directly Shortest ON pulse: 250ms Shortest OFF Pulse: 250ms
Alarm Sound Intensity	85dB, minimum, at 1m
Receiver	Dual antenna diversity

Electrical

Electrical Connections	Standard US outlet
------------------------	--------------------

Environmental

Operating Temperature	0° to 120°F (-17.7° to 49°C)
-----------------------	------------------------------

By making home technology simple, Clare provides exclusive benefits to integrators, builders, and homeowners. We offer innovative home automation solutions, Class D amplifiers, media distribution, controllable lighting, and IP CCTV components. For more information, visit clarecontrols.com.