



ClareOne Z-Wave Indoor Siren

CLR-C1-ZW-SRN

Intrusion



Specifications	
Compatible panel	ClareOne (CLR-C1-PNL1)
Repeater	Yes
Z-Wave plus	Yes
Max volume	105 dB, reduced in battery powered mode
Input voltage	120V 60Hz, Max: 30mA
Battery type	Built-in Lithium 430mAh
Battery life	3 hours total use
Alarm power	1.7W
Max standby power	0.7W
Operating temperature	32 to 113°F (0 to 45°C)
Relative humidity	95% non condensing
Dimensions (W x H x D)	3.3 x 2.2 x 1.8 in. (83.2 x 55.9 x 45.7 mm)
Certifications	FCC: 15.109 Class B 15.231

The ClareOne Z-Wave Indoor Siren extends the audible security alarm tone to additional areas of the home, to make sure all occupants are informed of alarm events. Visual alerts are given by three front-facing LEDs. The siren uses Z-Wave Plus.

Performance Highlights:

- Extend audible alarm siren to areas of the home that are away from the ClareOne Panel
- 105 db max volume
- Battery backup for up to 3 hours of continuous use
- Z-Wave Plus

By making home technology simple, Clare provides exclusive benefits to integrators, builders, and homeowners. We offer innovative home automation solutions, wireless security, controllable lighting, and IP CCTV components. For more information, visit clarecontrols.com.