



ClareVue Lighting 5-Scene Keypad

CL-5KP-W-20 / CL-5KP-LA-20



The ClareVue 5-Scene Keypad provides pushbutton local or automated control over up to 5 scenes. LEDs on each button indicate whether the scene is on or off. A keypad can be placed at entrance ways or any convenient location where control of multiple scenes is desired.

ClareVue 5-Scene keypads use standard 120 VAC 60 Hz house wiring, and fit into standard wall boxes.

- Easily configure Scenes for keypads with the ClareVue Lighting Wizard
- Activates up to 5 scenes associated with ClareVue devices and the ClareHome automation solution
- Blue LED provides scene status notification
- Matches other ClareVue lighting components
- Available in White (W) or Light Almond (LA)

Technical Specifications

General

Rating	120 VAC, 60 Hz
Z-Wave	Uses 300 Series Z-Wave Chip @ 40 Kbs
Load Type	n/a
Wattage	n/a
Testing & Code Compliance	UL/cUL Listed 6B28 NOM 426 Complies with FCC Part 15, Class B Z-Wave Certified
Terminations	Three 6" pre-stripped wire leads for line, neutral and ground
Operating Temperature	32°F to 104°F (0°C to 40°C)

The ClareVue Lighting Wizard Makes Setup Easy

Wizard guides the installer through step by step:

- Adding ClareVue Lighting devices – dimmers, switches, keypads, receptacles – to a Fusion project
- Including devices into the Z-Wave network
- Setting up dimmer max/min levels and ramp rate
- Creating new lighting Scenes
- Removing ClareVue devices from the network and the project

Easily configure ClareVue devices:

- Setting up 3-way and multi-location control
- Create a virtual keypad on the UI with the same controls

Configure project lighting offsite in advance:

- Easily add them all to the Z-Wave network once onsite
- Deploy the project and go!

By making home technology simple, Clare provides exclusive benefits to integrators, builders, and homeowners. We offer innovative home automation solutions, Class D amplifiers, media distribution, controllable lighting, and IP CCTV components. For more information, visit clarecontrols.com.