



ClareVue Plug-In Dimmer

CVL-PLD-10



Specifications	
General	
Rating	120 VAC, 60 Hz
Z-Wave	Signal frequency 908.4/916 MHz
Z-Wave Outlet Load	Max load for the Z-Wave controlled outlet: 300W incandescent / 100W dimmable CFL/LED
Pass-Through Outlet Load	Max load: 1800W
Total Max Load	Both outlets combined: 15 Amps, 1800W resistive
Operating Temperature	-32 to 104° F (-0° to 40° C)
Usage	Indoor only
Code Compliance	cUL Listed Complies with FCC and Industry Canada Regulations

The ClareVue Plug-In Dual Outlet Dimmer allows for dimming controls of lamps up to 300W for incandescent, and 100W for CFL, and LED light bulbs. The space efficient design does not block the lower outlet on duplex receptacles and allows the user to route their cables and plugs to the side. Remotely and manually control ON/OFF and dimming of compatible light bulbs.

- One Z-Wave controlled AC outlet
- One always-on pass-through outlet
- Works with dimmable LED, CFL, and incandescent bulbs
- Remote ON/OFF, dimming control via Z-Wave outlet
- Manual ON/OFF, dimming control with top push-button
- Z-Wave Plus certified



*Space efficient design doesn't block lower outlet

By making home technology simple, Clare provides exclusive benefits to integrators, builders, and homeowners. We offer innovative home automation solutions, Class D amplifiers, media distribution, controllable lighting, and IP CCTV components. For more information, visit clarecontrols.com.