

! IMPORTANT! G7x NEEDS TO BE PAIRED



Before the G7x in this box can be used, it will first need to be paired to a your organization's Bridge network. Pairing devices is a one-time setup step. After being paired, G7x and any Bridge in your organization will automatically connect to one another when on and in range.

Before getting started you will need:

- G7 Bridge with a solid green light
- G7x devices you wish to pair

Green connectivity light



How do I pair new G7x devices with my organization's Bridge network?

G7x will let you know it needs to be paired by sounding a yellow warning alarm and by showing *pairing needed* in the banner. To pair:

1. Turn on G7 Bridge
2. Press OK on G7 Bridge to open Bridge's menu
3. Use the up and down arrows to navigate to *pair new loners* and press OK
4. Use the up and down arrows to navigate to *start* and press OK
NOTE: if your G7 Bridge will not allow you to start pairing, this means it has not yet been assigned a network key for your organization. Please contact our Customer Care team.
5. G7 Bridge's screen will say *pairing started* as it looks for devices
6. Turn on up to 5 G7x devices.
NOTE: G7 Bridge can only connect to 5 G7x devices at once.
7. When G7x has been paired, you will notice the following:
 - G7 Bridge's main screen will show that it has connected devices
 - The yellow warning alarm on G7x will silence
 - G7x's green connectivity light will be solid (not flashing)
 - You will receive a message on G7's screen that reads *pairing succeeded* and shows your organization's Bridge network key
8. Press OK on G7 Bridge to stop pairing once all necessary devices have been paired

If you are pairing more than 5 G7x devices, repeat steps 2-7 for all G7x devices.

If you are having difficulties pairing, you can try the following:

- Ensure that G7 Bridge has a solid connectivity light
- Place G7x and Bridge within 1-3 meters of one another. If devices are too close, they may have difficulties connecting.
- Ensure you aren't trying to pair more than 5 G7x devices at once. G7 Bridge can only connect to 5 G7x devices at a time.