



REALFICTION™

## **CHANGE IN DREAMOC XL3 SOFTWARE WITH THE NEW SCREEN (LG43SE3KE-B) - FAIL\_OVER**

**For the Dreamoc XL3 with the new screen (LG43SE3KE-B), we have now found a way to make USB playback without creating a playlist.**

When adding content to your USB you need to add a FAIL\_OVER folder and place your content inside the folder.

### **CREATING A FOLDER ON YOUR USB WITH FAIL\_OVER**

This feature automatically playback the video files in the FAIL\_OVER folder, if the screen is programed to FAIL\_OVER mode. All product from REALFICTION with series no higher than BN904-0001, is programed to use FAIL\_OVER mode from the factory.

#### **Create a folder on your USB stick**

1. Put your USB stick in your computer
2. Add a folder to the USB stick called FAIL\_OVER (it is important it is written in capital letter and with hyphen between.
3. Add your content inside the folder
4. Eject the USB and place in the Dreamoc XL3

#### **If your Dreamoc XL3 is not programed to FAIL\_OVER, this can be done the following way**

1. Click the EXIT button on the remote control
  - a. No signal menu will now appear on the screen
2. Click the Settings button on the remote control (the tooth wheel)
3. Choose EZ Settings
4. Move the cursor to "Fail Over" icon and click OK
5. In the Fail Over menu make the following settings:
  - a. Mode = Auto
  - b. USB = Movie
6. Chooze back. The content in the FAIL\_OVER folder will now be played.