

	<b>PRODUCT SPECIFICATION</b>	Doc Number	WM8923-H
		<b>Part Number: WM8923-H</b>	
		Date	June 24, 2012
		Revision	4.0

## 1. Battery Information

Replaces OEM battery: RNN4006  
Radio model: Motorola XTS 3000 and XTS5000  
Voltage: 7.5  
Capacity: 2700 Mah  
Cell Chemistry: Ni-Mh  
Cell Origin: Japan/China



## 2. Pack Protection

Protection Circuit: Over Voltage, Over Current and Under Voltage Protection, Diode Protection for reverse charging. Pack includes thermistor, and resistor.

## 3. Operating temperature condition:

Charge: 0 to 40°  
Discharge: -20 to 60°  
Recommend Storage: -20 to 25°

## 4. Certification:

ISO Certified

## 5. Warranty information:

*Battery is warranted to maintain 80% of its rated capacity for 12 months from the date of shipment and to be free from any manufacturing and workmanship defects for 24 months prior to any usage.*

## Precautions:

Do not short circuit, do not disassemble; keep away from heat and do not dispose in fire.